



### Product Description

2 Hours Emergency Conversion Power Kits (3 hours optional) for LED Lamp with Build-in Driver

It can operate with build-in DC driver , Slim size inverter and battery can build-in to your batten fitting (or external slim size remote metal box with white powder coated , ) . Low voltage cut-out and variable rate charger inverter to keep the battery long life.

2小时紧急转换电源套件（3小时可选），用于带内置驱动器的LED灯。它可以使用内置直流驱动器，超薄尺寸的逆变器和电池内置到您的板条配件（或外部超薄型远程金属盒，白色粉末涂层，）。低压切断和可变速率充电器逆变器，以保持电池长寿命。

<b>Product Name/产品名称</b>	AMLED-2PL
<b>Dimension/尺寸</b>	330mm*60mm*85mm
<b>Made of Operation</b>	Maintained Type / Non-Maintained Type
<b>Recharge Period</b>	12 Hours
<b>Transfer Time</b>	<0.3s
<b>Main Voltage</b>	A/C 220V 50Hz +6%-10%
<b>Battery/电池</b>	Seal Maintenance free type Ni-CAD/ Ni-MH Rechargeable battery 9.6V 2000mah
<b>Emergency Output</b>	30%
<b>Operation Temp</b>	0 °C to 50 °C to
<b>Lamp Source/光源</b>	LED
<b>Wattage/瓦数</b>	Max. 39W
<b>Available Color/外壳颜色</b>	White
<b>Shell Material/外壳材质</b>	Aluminum
<b>IP Rating/防护等级</b>	IP20
<b>Certification/证书</b>	BS 5266 BS EN 60598-2-22 BE EN 61347-2-7 / 60925 ICEL:1001: Part II Hong Kong Fire Service Department: PPA 104 & PPA104A (4th Revision)